

 ICOM

IC-M85E

VHF MARINE TRANSCEIVER

*Marine and PMR Hybrid
for Professional Use*



Ultra Compact and Powerful Marine Handheld with PMR Features



[Actual Size]



VHF MARINE TRANSCEIVER
IC-M85E

Compact and Lightweight

The IC-M85E is the most compact (W×H×D: 56 × 92 × 29 mm) and lightweight (weight: 246 g (with BP-290, FA-SC58V and MBB-3)) commercial grade marine and land mobile hybrid radio in the world*.
* As of November 2017, researched by Icom.

Covering 136–174 MHz PMR Frequency

In addition to VHF marine channels, the IC-M85E covers 136–174 MHz PMR channels. Up to 100 programmable channels are available for PMR use. Each channel is programmable with CTCSS and DTCS tone.

700 mW Powerful Audio

Despite its compact body, the IC-M85E delivers 700 mW of loud audio. Clear communications is vital in noisy environments.

Private Conversation

The radio has a built-in Voice Scrambler and provides private communication between stations (32-code, compatible with UT-112 voice scrambler unit).

Automated Emergency Alarm

The IC-M85E has three emergency related functions: the MOB Alarm, Man Down and Lone Worker functions. If one of these functions are activated, the radio automatically makes an emergency alarm.

Instant Operation with Multi-Function Button

Channel group changing (Marine ⇄ PMR) or the scrambler function ON/OFF can be assigned in the multi-function button on the top panel*. The Key lock function can be activated by holding the button.
* Ask your dealer for details.

IP67 and MIL-STD Rugged Construction

The IC-M85E is built durable to endure 1 m submersion for 30 minutes and dust-tight protection. The radio also passes MIL-STD-810 specifications.

And More

- AquaQuake™ prevents audio degradation from a water-logged speaker
- Internal VOX capability for hands-free operation
- 14 hours of long battery life (TX: RX: Standby=5:5:90.)
- 5 W output power
- The self check function checks internal temperature, and connected battery voltage (over voltage detection)
- Monitor function • Priority scan function
- Dual/Tri-watch function for monitoring CH16 and/or call channel
- Favorite channel function for quick access to often used channels

Supplied accessories;





BP-290 battery pack BC-227 rapid charger BC-123S* AC adapter FA-SC58V antenna MBB-3 belt clip Hand strap
* SE for Europe plug, SUK for UK plug, SV for Australia plug.

Variety of Audio Accessories




Waterproof Speaker-Microphones



Hands-Free Operation with Headsets







Earphones and Speaker Microphones for Noisy Environments




* With 3.5 mm plug.

Stylish Operation with Tie-Clip Microphone and Earphones



* With 2.5 mm plug.

Covert Earphone



OPTIONS


BATTERY PACK AND CASE



BP-290
Rechargeable Li-ion battery with intelligent reporting. 1910 mAh (min.) 2010 mAh (typ.) IP67 Waterproof

BP-291
Battery case LR6 (AA) x 5. IP54 Water resistance


MULTI-CHARGER



BC-214 **BC-157S** **AD-132N**

Charges up to six BP-290 batteries in 2.8 hours (approx.). AD-132N is supplied with BC-214, depending on version.


CONNECTABLE TYPE CHARGER



BC-226 **BC-228** **BC-225**

Charges the BP-290 in 2.7 hours. (approx.) Connects up to six BC-226 units.

INTELLIGENT CHARGER **DESKTOP CHARGERS**



BC-225 **BC-123S*** Shows the charging information with LED lighting. Charges the BP-290 in 2.5 hours. (approx.)

BC-227 **BC-123S*** Charges the BP-290 in 2.7 hours. (approx.)

BC-219N **BC-123S*** Charges the BP-290 in 2.5 hours. (approx.)


* SE for Europe plug. SUK for UK plug. SV for Australia plug.

BELT CLIPS



MBB-3 **MB-136**
Alligator type. Swivel type.

BELT HANGERS



MB-96N **MB-96F** **MB-96FL**
Swivel type. Fixed type. Long type.

ACC ADAPTOR




AD-118
14-pin multi-connector to 6-pin Hirose connector

CARRYING CASES



LC-187 **LC-188**
Hard type. Hard type.
Charging is possible while the case is attached.

CIGARETTE LIGHTER CABLE & POWER SUPPLY CABLES **ANTENNA**



CP-23L For use with the BC-219N or BC-227.

OPC-515L For use with the BC-219N, BC-225 or BC-227.

OPC-656 For use with the BC-214.

FA-SC58V

SOFTWARE
• **RS-BC225** : Intelligent charger software for Windows® PC. For use with BC-225.

SPECIFICATIONS

		IC-M85E	
GENERAL		Marine channels	PMR channels
Frequency coverage Tx/Rx		156.000–161.450 MHz 156.000–163.425 MHz	136.000–174.000 MHz
Usable channel groups, Number of channels		INT, USA* channels (*Varies according to version)	100 PMR channels
Type of emissions	EUR, UK FRG	16K0G3E	16K0F3E/8K50F3E 14K0F3E/8K50F3E
Channel spacing	EUR, UK FRG	25 kHz	25/12.5 kHz 20/12.5 kHz
Power supply requirement			
Current drain (approximate)		7.2 V DC nominal	
Tx (at 5 W)		1.5 A	
Rx Max. audio		0.45 A	
Antenna impedance		50 Ω	
Operating temperature range		-15 °C to +55 °C	-25 °C to +55 °C
Dimensions (W×H×D)		56 × 92 × 29 mm (With BP-290)	
(Projections not included)			
Weight (approximate)		246 g (with BP-290, FA-SC58V and MBB-3)	

TRANSMITTER

Output power (at 7.2 V DC)		5/3/1 W	5/3/1 W
Max. frequency deviation	EUR, UK	±5.0 kHz	±5.0 kHz (Wide)
	FRG		±2.5 kHz (Narrow)
Frequency stability	±1.5 kHz		
	Spurious emissions		
		0.25 μW (≤2 GHz), 1.0 μW (>2 GHz)	
Residual modulation	40 dB		40 dB (Wide)
			34 dB (Narrow)
Audio harmonic distortion		10% (at 60% deviation)	
Modulation limiting		60–100% of maximum deviation	

RECEIVER

Sensitivity (at 20 dB SINAD)	-4 dBμ emf typical	-4 dBμ emf typical (Wide)	-2 dBμ emf typical (Narrow)
Adjacent channel selectivity	70 dB	70 dB (Wide)	60 dB (Narrow)
Spurious response	70 dB		
Intermodulation	68 dB	65 dB	
Hum and noise	40 dB	40 dB (Wide), 34 dB (Narrow)	
Audio output power	Internal SP	700 mW typical (at 10% distortion with 12 Ω load at 1 kHz)	
	External SP	700 mW typical (at 10% distortion with 8 Ω load at 1 kHz)	

Measurements made in accordance with EN 301-178 or EN 300 086. All stated specifications are subject to change without notice or obligation.

Applicable U.S. Military Specifications & IP Rating

Standard	MIL 810 G	
	Method	Procedure
Low Pressure	500.5	I, II
High Temperature	501.5	I, II
Low Temperature	502.5	I, II
Temperature Shock	503.5	I-C
Solar Radiation	505.5	I
Rain Blowing/Drip	506.5	I, III
Humidity	507.5	II
Salt Fog	509.5	-
Dust Blowing	510.5	I
Immersion	512.5	I
Vibration	514.6	I
Shock	516.6	I, IV

Also meets equivalent MIL-STD-810-C, -D, -E and -F.

Ingress Protection Standard

Dust & Water	IP67 (Dust-tight and waterproof protection)
--------------	---

Icom, Icom Inc. and the Icom logo are registered trademarks of Icom Incorporated (Japan) in Japan, the United States, the United Kingdom, Germany, France, Spain, Russia, Australia, New Zealand and/or other countries. AQUAQUAKE is a trademark of Icom Incorporated. Windows is either a registered trademark or a trademark of Microsoft Corporation in the United States and/or other countries. All other trademarks are the properties of their respective holders.

Icom Inc. 1-1-32, Kamiminami, Hirano-Ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013 www.icom.co.jp/world **Count on us!**

Icom America Inc.
12421 Willows Road NE,
Kirkland, WA 98034, U.S.A.
Phone: +1 (425) 454-8155
Fax: +1 (425) 454-1509
E-mail: sales@icomamerica.com
URL: <http://www.icomamerica.com>

Icom (Europe) GmbH
Communication Equipment
Auf der Krautweide 24
65812 Bad Soden am Taunus, Germany
Phone: +49 (6196) 76685-0
Fax: +49 (6196) 76685-50
E-mail: info@icomeurope.com
URL: <http://www.icomeurope.com>

Icom France s.a.s.
Zac de la Plaine,
1 Rue Brindejonc des Moulinais, BP 45804,
31505 Toulouse Cedex 5, France
Phone: +33 (5) 61 36 03 03
Fax: +33 (5) 61 36 03 00
E-mail: icom@icom-france.com
URL: <http://www.icom-france.com>

Your local distributor/dealer:

Icom Canada
Glenwood Centre #150-6165
Highway 17A, Delta, B.C.,
V4K 5B8, Canada
Phone: +1 (604) 952-4266
Fax: +1 (604) 952-0090
E-mail: sales@icomcanada.com
URL: <http://www.icomcanada.com>

Icom Spain S.L.
Ctra. Rubi, No. 88 "Edificio Can Castanyer"
Bajos A 08174, Sant Cugat del Valles,
Barcelona, Spain
Phone: +34 (93) 590 26 70
Fax: +34 (93) 589 04 46
E-mail: icom@icomspain.com
URL: <http://www.icomspain.com>

Icom (Australia) Pty. Ltd.
Unit 1 / 103 Garden Road,
Clayton, VIC 3168 Australia
Phone: +61 (03) 9549 7500
Fax: +61 (03) 9549 7505
E-mail: sales@icom.net.au
URL: <http://www.icom.net.au>

Icom Brazil
Rua Itororó, 444 Padre Eustáquio
Belo Horizonte MG,
CEP: 30720-450, Brazil
Phone: +55 (31) 3582 8847
Fax: +55 (31) 3582 8987
E-mail: sales@icombrasil.com

Icom (UK) Ltd.
Blacksale House, Altira Park,
Herne Bay, Kent, CT6 6GZ, U.K.
Phone: +44 (0) 1227 741741
Fax: +44 (0) 1227 741742
E-mail: info@icomuk.co.uk
URL: <http://www.icomuk.co.uk>